POWER IS OUR WORLD

About Product

IDEA generator sets are designed to be used as backup or continuous power supply. They are subjected to detailed load and performance tests in our production facilities in order to provide ideal performance and safe usage.

INDUSTRIAL RANGE

DATASHEET



Power Output Values


Voltage	Standby Power (ESP)			Prime Power (PRP)		
	kVA	kW	Ampere	kVA	kW	Ampere
400/231	1000 kVA	800 kW	1450	910 kVA	728 kW	1320


Standby Power (ESP): This rating is for the supply of continuous electrical power at variable load, in the event of utility power failure. No overload is permitted.


Prime Power (PRP): This rating is for the supply of continuous electrical power at variable load. There is no limitation on the annual hours in operation and 10% overload power can be supplied for 1 hour in 12.

Weight And Dimensions

Туре	Width x Length x Height (mm)	Weight (kg)	Fuel Tank (Lt)	Sound dB(A) @1mt
Open	2300x5000x2580 mm	6400 kg	1500 lt	-
Soundproofed	2300x5200x3200 mm	7800 kg	1500 lt	87







www.ideajenerator.com I info@ideajenerator.com

IDEA

POWER IS OUR WORLD

Engine



Frequency		50 Hz	
Output Rating	kW	886	
Manufacturer and Model		12V886TAD	
Fuel		Diesel	
Injection		Direct	
Aspiration		Turbocharged & Intercooled	
Cylinders		12	
Bore and Stroke	mm	138 x 168	
Displacement	lt	30,2	
Cooling		Water	
Engine Oil Specification		SAE 15W40	
Compression Ratio		14	
Engine Oil Capacity	lt	42	
Coolant Capacity (incl.radiator)	lt	155	
Governor		Electronical	
Air Filter		Dry element	
FUEL CONSUMPTION			
100 % Load	lt/h	196,3	
75 % Load	lt/h	151	
50 % Load	lt/h	100,6	
EXHAUST SYSTEM			
Maximum Temperature	°C	600	
Exhaust Gas Flow	m³/min	2 <mark>4</mark> 0	
Maximum Allowed Back Pressure	kPA	6	
Exhaust Flange Size (Internal Dia.)	mm	110	
AIR SYSTEM			
Intake Air Flow	m³/min	90	
Total Cooling Air Flow	m³/min	1 <mark>54</mark> 0	
STARTING SYSTEM		₩	
Starter Motor	kW	11	
Battery Capacity	Ah	2x120	
Auxiliary Voltage	V	24	

Alternator

Poles	4 pole		
Winding Connections	Star		
Insulation	Class H		
Enclosure	IP23		
Exciter System	Self regulating Brushless		
Voltage Regulator	AVR		
Steady State Voltage Regulation	± 1 %		
Bearing	Single bearing sealed		
Coupling	Flexible disc		
Cooling	Direct drive centrifugal blower fan		



POWER IS OUR WORLD

Control Panel IDP300

The new IDP300 genset controller is a cost effective modular genset controller ready for internet monitoring through plug-in modules.

INDUSTRIAL RANGE

DATASHEET

Its main advantages are multifunctionality, support for multiple topologies, harmonic analysis and detailed power measurements.



Software features are complete with easy firmware upgrade through USB port. The Windows based PC software allows monitoring and programming through USB, RS-485, RS-232, Ethernet and GPRS.

The Rainbow Scada web service allows monitoring and control of an unlimited number of gensets from a single central location.

Optional Equipments

Some Optional Equipment IDEA Provides with Generator Sets;

- Remote radiator applications,
- Automatic fuel filling system,
- Fuel tank, oil pan, instrument panel, alternator, coil heaters,
- Synchronization systems,
- Generator output fuse,
- Mains generator transfer switches,
- Seismic solutions,
- Remote monitoring
- Other requested solutions

Reference Standards

IDEA Generator Sets are CE approved and comply with the following standards;

- Power according to ISO 3046 and ISO 8528
- EN 12100, EN 13857, EN 60204
- 2006/42/CE Machinery Safety
- 2006/95/EC Low Voltage
- 2004/108/CE EMC
- Ambient reference conditions 1000 mbar, 25 °C, 30 % relative humidity ISO8528

All the information in this leaflet is intended for general purposes only. IDEA reserves the right to change the specifications without notice.



www.ideajenerator.com I info@ideajenerator.com