

### About Product

IDEA generator sets are designed to be used as backup or continuous power supply. They are subjected to detailed load and performance tests in our production facilities in order to provide ideal performance and safe usage.



### Power Output Values

Voltage	Standby Power (ESP)			Prime Power (PRP)		
	kVA	kW	Ampere	kVA	kW	Ampere
400/231	<b>400 kVA</b>	320kW	578	<b>360 kVA</b>	288 kW	520

**Standby Power (ESP)** : This rating is for the supply of continuous electrical power at variable load , in the event of utility power failure. No overload is permitted.

**Prime Power (PRP)** : This rating is for the supply of continuous electrical power at variable load. There is no limitation on the annual hours in operation and 10% overload power can be supplied for 1 hour in 12.

### Weight And Dimensions

Type	Width x Length x Height (mm)	Weight (kg)	Fuel Tank (Lt)	Sound dB(A) @1mt
Open	1300x3250x1800 mm	2900 kg	400 Lt	-
Soundproofed	1300x4500x2350 mm	3420 kg	400 Lt	80



### Engine

Frequency		50 Hz
Output Rating	kVA	405
Manufacturer and Model		Baudouin 6M21G400/5
Fuel		Diesel
Injection		Direct
Aspiration		Turbocharged and Aftercooled
Cylinders		6
Bore and Stroke	mm	127 x 165
Displacement	lt	12,54
Cooling		Water
Engine Oil Specification		SAE 15W40
Compression Ratio		16:1
Engine Oil Capacity(Sump Only)	lt	30
Coolant Capacity (incl.radiator)	lt	55
Governor		Electronic
Air Filter		Dry element
<b>FUEL CONSUMPTION</b>		
100 % Load	lt/h	82,1
75 % Load	lt/h	60,7
50 % Load	lt/h	41
<b>EXHAUST SYSTEM</b>		
Maximum Temperature	°C	740
Exhaust Gas Flow	m <sup>3</sup> /min	65
Maximum Exhaust Back Pressure	mBar	120
Exhaust Flange Size (Internal Dia.)	mm	100
<b>AIR SYSTEM</b>		
Intake Air Flow	m <sup>3</sup> /min	23,8
Air Intake Temperature Rise	°C	<15
<b>STARTING SYSTEM</b>		
Starter Motor	kW	7,5
Battery Capacity	Ah	2x100
Auxiliary Voltage	V	24

### Alternator

Poles		4 pole
Winding Connections		Star
Insulation		Class H
Enclosure		IP23
Exciter System		Self regulating Brushless
Voltage Regulator		AVR
Steady State Voltage Regulation		± 1 %
Bearing		Single bearing sealed
Coupling		Flexible disc
Cooling		Direct drive centrifugal blower fan




### Control Panel IDP300

The new IDP300 genset controller is a cost effective modular genset controller ready for internet monitoring through plug-in modules.

Its main advantages are multifunctionality, support for multiple topologies, harmonic analysis and detailed power measurements.

Software features are complete with easy firmware upgrade through USB port. The Windows based PC software allows monitoring and programming through USB, RS-485, RS-232, Ethernet and GPRS.

The Rainbow Scada web service allows monitoring and control of an unlimited number of gensets from a single central location.



### Optional Equipments

Some Optional Equipment IDEA Provides with Generator Sets;

- Remote radiator applications,
- Automatic fuel filling system,
- Fuel tank, oil pan, instrument panel, alternator, coil heaters,
- Synchronization systems,
- Generator output fuse,
- Mains generator transfer switches,
- Seismic solutions,
- Remote monitoring
- Other requested solutions

### Reference Standards

IDEA Generator Sets are CE approved and comply with the following standards;

- Power according to ISO 3046 and ISO 8528
- EN 12100 , EN 13857 , EN 60204
- 2006/42/CE Machinery Safety
- 2006/95/EC Low Voltage
- 2004/108/CE EMC
- Ambient reference conditions 1000 mbar, 25 °C, 30 % relative humidity ISO8528

All the information in this leaflet is intended for general purposes only. IDEA reserves the right to change the specifications without notice.

