

POWER IS OUR WORLD

About Product

IDEA generator sets are designed to be used as backup or continuous power supply. They are subjected to detailed load and performance tests in our production facilities in order to provide ideal performance and safe usage.

INDUSTRIAL RANGE

DATASHEET



Power Output Values


Voltage	Sta	Standby Power (ESP)			Prime Power (PRP)		
	kVA	kW	Ampere	kVA	kW	Ampere	
400/231	900 kVA	720 kW	1300	815 kVA	652 kW	1177	


Standby Power (ESP): This rating is for the supply of continuous electrical power at variable load, in the event of utility power failure. No overload is permitted.


Prime Power (PRP): This rating is for the supply of continuous electrical power at variable load. There is no limitation on the annual hours in operation and 10% overload power can be supplied for 1 hour in 12.

Weight And Dimensions

Туре	Width x Length x Height (mm)	Weight (kg)	Fuel Tank (Lt)	Sound dB(A) @1mt
Open	2300x3800x2000 mm	4500 kg	1500 lt	-
Soundproofed 2300x5200x3200 mm		5800 kg	1500 lt	86









POWER IS OUR WORLD

Engine



Frequency		50 Hz	
Output Rating	kW	793	
Manufacturer and Model		Baudouin 12M26G900/5	
Fuel		Diesel	
Injection		Direct	
Aspiration		Turbocharged and Aftercooled	
Cylinders		12 V	
Bore and Stroke	mm	150 x 150	
Displacement	lt	31,8	
Cooling		Water	
Engine Oil Specification		SAE 15W40	
Compression Ratio		15.7:1	
Engine Oil Capacity(Sump Only)	lt	109	
Coolant Capacity (incl.radiator)	lt	148	
Governor		Electronic	
Air Filter		Dry element	
FUEL CONSUMPTION			
100 % Load	lt/h	173,7	
75 % Load	lt/h	133,1	
50 % Load	lt/h	90,8	
EXHAUST SYSTEM			
Maximum Temperature	°C	750	
Exhaust Gas Flow	m³/min	1 <mark>49</mark> ,7	
Maximum Exhaust Back Pressure	mBar	75	
Exhaust Flange Size (Internal Dia.)	mm	200	
AIR SYSTEM			
Intake Air Flow	m³/min	60	
Air Intake Temperature Rise	°C	<5	
STARTING SYSTEM		₩	
Starter Motor	kW	10	
Battery Capacity	Ah	2x120	
Auxiliary Voltage	V	24	

Alternator

Poles	4 pole		
Winding Connections	Star		
Insulation	Class H		
Enclosure	IP23		
Exciter System	Self regulating Brushless		
Voltage Regulator	AVR		
Steady State Voltage Regulation	± 1 %		
Bearing	Single bearing sealed		
Coupling	Flexible disc		
Cooling	Direct drive centrifugal blower fan		





POWER IS OUR WORLD

Control Panel IDP300

The new IDP300 genset controller is a cost effective modular genset controller ready for internet monitoring through plug-in modules.

Its main advantages are multifunctionality, support for multiple topologies, harmonic analysis and detailed power measurements.



Software features are complete with easy firmware upgrade through USB port. The Windows based PC software allows monitoring and programming through USB, RS-485, RS-232, Ethernet and GPRS.

The Rainbow Scada web service allows monitoring and control of an unlimited number of gensets from a single central location.

Optional Equipments

Some Optional Equipment IDEA Provides with Generator Sets;

- Remote radiator applications,
- Automatic fuel filling system,
- Fuel tank, oil pan, instrument panel, alternator, coil heaters,
- Synchronization systems,
- Generator output fuse,
- Mains generator transfer switches,
- Seismic solutions,
- Remote monitoring
- Other requested solutions

Reference Standards

IDEA Generator Sets are CE approved and comply with the following standards;

- Power according to ISO 3046 and ISO 8528
- EN 12100, EN 13857, EN 60204
- 2006/42/CE Machinery Safety
- 2006/95/EC Low Voltage
- 2004/108/CE EMC
- Ambient reference conditions 1000 mbar, 25 °C, 30 % relative humidity ISO8528

All the information in this leaflet is intended for general purposes only. IDEA reserves the right to change the specifications without notice.



www.ideajenerator.com I info@ideajenerator.com